

## Stowing the monitors

The monitors cost £1,200 each and must be treated gently.

### On the firing point

Do not let plugs touch wet grass.

Remove each black cable from the monitor and from the “shooters junction box” by pressing the small “tab” on the silver XLR connector and pulling the connector gently in a straight line.

Coil the black cables **loosely and individually** and put in their container after drying them if necessary.

Pack the monitors in the grey plastic trunk.

Each monitor must be separated from the next by a piece of foam. Store alternate monitors upside down to make best use of the space.

Loosely coil the grey cabling with shooter’s junction boxes attached and place it its container with the 6 black monitor cables. Pack the monitor covers in their bag in such a way that no transparent face is outermost.

### In the armoury

**If there has been any wet weather at all, the cables and monitors must be checked for moisture before leaving them in store.**

The monitors should never be wet. If one has any moisture at all dry it at once and store it out of the box.

If wet, the cabling with “shooters junction boxes” attached must be dried and stored out of its container.

Always leave the lid of the grey “trunk” open in the armoury so any unseen moisture can evaporate.